

Figure 6.27: Plots of magnitude of optimal sensitivity S and of step response for design problem 2.

The set S_ω of all possible $T(j\omega)$ that satisfy both (6.39) and (6.40) is a subset of the complex plane. This set can be described as follows:

$$S_\omega = \{\ s :\ max(\ 2|s-1|\ ,\ \frac{5}{6}|s|\ ) \leq 1\ \}$$

Note that S_ω is the intersection of two disks. Another important feature of S_ω is that its boundary has " corners ".

6.5.2 Performance from competing constraints

The function Γ in (6.36) is not smooth even if the functions Γ_k are smooth. This can be seen from the *sublevel sets*

$$S_\omega(\gamma) = \{\ s :\ \Gamma(\omega, s) \leq \gamma\ \}, \tag{6.41}$$